

Code No: 137CF

JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD

B. Tech IV Year I Semester Examinations, December - 2019

ELECTRONIC MEASUREMENTS AND INSTRUMENTATION

(Electronics and Communication Engineering)

Time: 3 Hours

Max. Marks: 75

Note: This question paper contains two parts A and B.

Part A is compulsory which carries 25 marks. Answer all questions in Part A. Part B consists of 5 Units. Answer any one full question from each unit. Each question carries 10 marks and may have a, b, c as sub questions.

PART-A

(25 Marks)

- 1.a) Define gross errors and systematic errors. [2]
- b) State specification of instruments [3]
- c) Define distortion [2]
- d) State the applications of pulse and square wave generators. [3]
- e) How frequency can be measured using oscilloscope? [2]
- f) How frequency can be measured using Lissajous figures. [3]
- g) Explain the principle of piezo transducer. [2]
- h) Draw Syncro diagram. [3]
- i) What is meant by balancing a bridge? [2]
- j) Draw the block diagram of data acquisition system. [3]

PART-B

(50 Marks)

- 2.a) Explain the basic principle of a shunt type ohmmeter.
- b) Calculate the maximum percentage error in the sum and difference of two voltage measurements when $V_1 = 100\text{v} \pm 1\%$ and $V_2 = 80\text{v} \pm 5\%$. [6+4]

OR

- 3.a) Define Accuracy, Precision, Resolution and Limiting error.
- b) Design a range switch for an ammeter, with an internal resistance $r_m = 100\Omega$ and a full scale deflection of $I_m = 1\text{mA}$. The meter is to measure in the ranges of 10mA, 100mA and 500mA. [6+4]

- 4.a) What are the main requirements of sine wave signal generator in instrumentation?

- b) Explain with suitable block diagram how an AF sine/ square generator works. [4+6]

OR

- 5.a) What is wave analyzer? Explain how it analyzes the harmonics?

- b) Enlist the various applications of spectrum analyzer along with the description of its working. [6+4]

8R 8R 8R 8R 8R 8R 8R

- 6.a) State the standard specification of a sample CRO.
b) Explain the operation of a sampling oscilloscope with a neat block schematic diagram. What is its advantage over the conventional oscilloscope? [4+6]

8R 8R 8R 8R 8R 8R 8R

- 7.a) Explain the block diagram of a vertical deflection system and explain the function of each block.
b) Explain the following CRO controls.
i) Focus ii) Trigger and calibration. [6+4]

8R 8R 8R 8R 8R 8R 8R

- 8.a) A transducer that measures force has nominal resting resistance of $300\ \Omega$ and is excited by 7.5V . When a 980 dyne force is applied, all four equal resistance bridge elements change resistance by $5.2\ \Omega$. Find the output voltage E_o .
b) Draw the various kinds of thermocouple junctions and their sheaths and discuss the seeback effect in thermocouple. [4+6]

OR

8R 8R 8R 8R 8R 8R 8R

- 9.a) Draw the diagram of strain gauge and explain the principle of measurement.
b) Draw the various kinds of thermometers and explain the principle of operation. [5+5]

8R 8R 8R 8R 8R 8R 8R

- 10.a) The basic AC bridge consists of the following constants:
AB: $R=400\ \Omega$, BC: $R=150\ \Omega$, CD: unknown and DA: $R=100\ \Omega$ in series with $L=10\text{mH}$. Oscillator frequency is 1KHz . Determine the constants of arm CD.
b) What is double Kelvin bridge? Derive the expression for the unknown resistance. [4+6]

OR

8R 8R 8R 8R 8R 8R 8R

- 11.a) Explain how LVDT is used to measure linear displacement.
b) How moisture in the air can be measured using transducers. [5+5]

--ooOoo--

8R 8R 8R 8R 8R 8R 8R

8R 8R 8R 8R 8R 8R 8R

8R 8R 8R 8R 8R 8R 8R